CHRISTIE LITES

Christie Lites 208v Socapex pin-out

Christie Lites' Moving Light/208v Distros are wired using a unique Socapex pin-out to avoid accidents if a 120v breakout is attached in error.

Christie Lites breakouts MUST be ordered when using non – Christie Lites cabling.

Please note that Christie Lites 208v breakouts use a PowerCON TRUE1 connector. L6-15 or L6-20 adapters are available on request.

Specific pin-out details are shown below:

Socapex Pin Number	Circuit Number
1	Circuit 1 Hot
2	Circuit 2 Hot
3	Circuit 1 Hot
4	Circuit 2 Hot
5	Circuit 3 Hot
6	Circuit 4 Hot
7	Circuit 3 Hot
8	Circuit 4 Hot
9	Circuit 5 Hot
10	Circuit 6 Hot
11	Circuit 5 Hot
12	Circuit 6 Hot
13	Circuit 1 Ground
14	Circuit 2 Ground
15	Circuit 3 Ground
16	Circuit 4 Ground
17	Circuit 5 Ground
18	Circuit 6 Ground
19	Shell

Note that all grounds are bussed together